Loading the PCStage USB Full driver.

1. Plug the PCStage interface. The computer should recognise that the interface has been connected and prompt you for a 'driver':



2. Select the "Install from a list or specific location (Advanced)" and click <next>. This screen will appear:



3. Tick the "Include this location in the search" box and then <Browse> your computer to end up in location you installed the PCStage program. When you have selected the USB directory, <OK>.

Browse For Folder		
Select the folder that contains drivers for your hardware.		
🛅 PC thermometer 🛛 🔼		
🖃 🚞 PCStage471		
🚞 Example		
🚞 Fixtures		
🚞 Parallel Port 💳		
🚞 Plugins		
🔁 USB		
To view any subfolders, click a plus sign above.		
OK Cancel		

4. This will close the 'browse for folder' window and return you to the previous 'found new hardware':



5. Click <Next>.



6. Click <Continue Anyway>



And that's done.

7. Now, start PCStage (or restart it if already running) and select <PCStage> from the menu bar and then <Preferences>:



8. Select <DMX> and then <USB> from the drop down list:

V Preferences	×
Auto Save Changed Items Colours Crossfades Cue Logging DMX Faders Internet Master Level MIDI Miscellaneous New Items Paths Serial I/O	Average 1
	🖌 OK 🦿 Help 🕺 Cancel 🍃

- 9. Click <OK> and you're done.
- 10. The Green DMX out light on your interface should be lit as confirmation all is OK.